

COMBI INVERTER/ CHARGER & GENERATOR CONSUMER UNIT

Designed for larger AC installations with a Combi Inverter/Charger, shorepower and an onboard generator. Shorepower and Generator power is fed to dedicated RCDs and then through an automatic changeover switch. A timer is provided to delay generator switch over (and allow generator to warm up before load is applied).

Our 'Box Clever' consumer units come equipped with Type A RCDs/RCCBs, designed to provide advanced protection in modern electrical systems. Unlike traditional Type AC devices, which are now obsolete in many applications, our units are fully optimised for installations where DC components are installed alongside AC wiring systems (e.g. Solar, Inverters & Batteries).

By offering cutting-edge safety as standard, we ensure compliance with the latest industry standards while delivering a smarter, safer solution for evolving electrical environments.

- **Pre-wired AC Distribution Boxes**
- **Massively reduces complexity of installing AC electrics**
- **Ensures reliability, correct wiring & safety**
- **Reduces installation time and cost**
- **IP66 Rated cabinets**
- **5 year warranty**



PART

15-3027

SHORE RCD

40A 30MA

GENERATOR RCD

63A 30MA

CHANGEOVER RATING

63A

SHORE/GEN OUTPUT

16A

COMBI UNIT RCD

25A 30MA

COMBI OUTPUT ONE

10A

COMBI OUTPUT TWO

10A

DIMENSIONS (MM)

310 x 427 x 151 (W x H x D)